




4路WiFi智能开关

型号：Sonoff 4CH



产品参数:

WiFi标准：2.4GHz b/g/n
输入电压：交流 90~250V
输出电压：交流 90~250V
单路最大负载：交流 220V 10A
最大总负载：交流 220V 16A

使用该设备前请检查以下事项：

- 您的智能手机或平板已连接上一个能上网的2.4G WiFi。
- 使用安卓系统的手机或平板，系统必须是4.0以上版本。
- 使用苹果手机或iPad必须能够访问APP商店并下载APP。
- 如果您的无线路由器设置了MAC地址过滤，请先进入路由器后台关闭MAC过滤功能。



产品使用说明

- 1 在各应用市场搜索“易微联”或扫码下载安装。




下载免费“易微联”APP


- 2 安装过程如有提示权限请求请选择允许。
- 3 注册账号并登录易微联。

- 4 按照设备外壳指示正确接线。


注：本设备的开关原理是通过控制电路火线的通断，从而实现电器工作和停止。本设备必须零火线供电，设备才能正常工作。如无地线可不接。



- 4.1 控制4路电器或插座示例（如无地线可不接）



- 4.2 控制单火线开关接线方法（比如灯具开关）



- 5 APP添加设备：长按任一通道的手动按钮大约7秒，直到WiFi指示灯快闪（闪两下亮一秒），松开。此时设备处于等待配对添加状态。



- 6 进入易微联，点击APP上的添加按钮 +

- 7



- 8 输入手机当前连接的WiFi密码，下一步。

- 9 待APP自动添加完成，给设备命名，完成添加。

- 10 当设备的WiFi指示灯长亮，即可进行远程遥控。




ewelink.coolkit.cc
扫码阅读常见问题和帮助



4 CHANNEL WIFI SWITCH

Model：Sonoff 4CH




Parameter:

WiFi standard: 2.4GHz b/g/n
Input voltage: 90-250V AC
Output voltage: 90-250V AC
Max. load: 220V 10A/gang
Max. total load: 220V 16A


Checklist before using the device

- Your smart phone or tablet has connected to a 2.4G WiFi with internet.
- You have the correct WiFi password.
- Your smart phone or tablet must have access to APP Store, Google Play.
- Make sure your router is MAC-open.



User Guide


- 1 Start with "Ewelink" APP.




- 2 Register an Ewelink account.
- 3 If you have Ewelink account, just log in.

- 4 Wiring instructions:

ON/OFF operating principle:
The connected appliances work/stop through live wire power on/off. The device must be powered by L and N. Earth wire is not essential.



- 4.1 Appliances Wiring Instruction. E is not essential.



- 4.2 One wire output instruction (Eg: light).

- 6 Press one of the buttons for 7s until the WiFi LED blinks like this: blinks 3 times and on repeatedly.



- 6 Tap + on Ewelink app.

- 7 For Android, select the first one. For iOS, select the pairing method according to LED blinking way.

- 8 Input your WiFi SSID & password.

- 9 Name your device to complete.

- 10 When the WiFi LED is on, the device is online. Start to control now!



Scan to download Ewelink free APP



Scan to read the detailed user guide